

V7-RUR5

V7 Option Switch Settings: 1 (Special Pulse/ICT/MDB)

Supported bill Ruble 10, 50, 100, 500, 1000 5bills.

V7 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
★ Reject Ruble 10 (Note 1.)	ON							
★ Accept Ruble 10 (Note 1.)	OFF							
★ Reject Ruble 50		ON						
★ Accept Ruble 50		OFF						
★ Reject Ruble 100			ON					
★ Accept Ruble 100			OFF					
★ Reject Ruble 500				ON				
★ Accept Ruble 500				OFF				
★ Reject Ruble 1000					ON			
★ Accept Ruble 1000					OFF			
★ Reserved						ON		
★ Reserved						OFF		
★ Harness Disable							ON	
★ Harness Engble							OFF	
★ Inhiblit Active High								ON
★ Inhibit Active Low								OFF

◆ Factory configuration has all switches in the OFF position.

V7 Interface Settings: 2 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ 1 pulse / Ruble 10	OFF	OFF		
2 pulse / Ruble 10	ON	OFF		
5 pulse / Ruble 10	OFF	ON		
10 pulse / Ruble 10	ON	ON		
★ 50ms on / 50ms off			OFF	OFF
60ms on / 300ms off			ON	OFF
30ms on / 50ms off			OFF	ON
150ms on / 150ms off			ON	ON

★ Manufacture setting

V7 Interface Settings: 2 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ 1 pulse / Ruble 50	OFF	OFF		
2 pulse / Ruble 50	ON	OFF		
5 pulse / Ruble 50	OFF	ON		
10 pulse / Ruble 50	ON	ON		
★ 50ms on / 50ms off			OFF	OFF
60ms on / 300ms off			ON	OFF
30ms on / 50ms off			OFF	ON
150ms on / 150ms off			ON	ON

★ Manufacture setting

V7-RUR5

V7 Interface Settings: 3 (ICT)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
★ ICT Interface		OFF	ON	
★ Reserved				ON
				OFF

V7 Interface Settings: 3 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
MDB Interface		OFF	OFF	
ICT Interface		OFF	ON	
★ Reserved				ON
				OFF

V7 Interface Settings: 3 (MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON	OFF	
★ MDB Interface		OFF	OFF	
ICT Interface		OFF	ON	
★ Reserved				ON
				OFF

Currency Assign Data

Interface Bill value	ICT	Pulse	MDB
BV1	Ruble 10	Ruble 10	Ruble 10
BV2	Ruble 50	Ruble 50	Ruble 50
BV3	Ruble 100	Ruble 100	Ruble 100
BV4	Ruble 500	Ruble 500	Ruble 500
BV5	Ruble 1000	Ruble 1000	Ruble 1000

Note: (1) Dip Switch 1 is for Pulse.

When SW1 Dip1 is OFF(Accept 10 Rubles),
Pulse → 10 Rubles=1 Pulse, 50 Rubles=5 Pulse, 100 Rubles=10 Pulse,
500 Rubles=50 Pulse, 1000 Rubles=100 Pulse....

When SW1 Dip1 is ON(Reject 10 Rubles),
Pulse → 50 Rubles=1 Pulse, 100 Rubles=2 Pulse, 500 Rubles=10 Pulse,
1000 Rubles=20 Pulse....